

Trigon Electronic Doorman T.E.D. Option (patent pending)



“This is TED the electronic doorman, please state your name or business and I will contact the resident for entry approval.”

Description and Operation:

The Trigon Electronic Doorman (patent pending) is a telephone entry option available on any Trigon entry telephone that allows the resident to determine the name or business of the visitor without actually talking to the visitor. The door unit, through a sophisticated combination of microprocessors and voice processors becomes a virtual doorman intermediary between the visitor and the resident as follows:

- –Once the resident code is determined and entered, T.E.D answers with one of three greetings as follows:
 - –**“Good afternoon, I’m TED The Electronic Doorman, please state your name or your business and I will contact your party for entry approval.”**
- –The visitor is given 10 seconds to record name or business then T.E.D. responds with:
 - –**“Please stand by while I contact your party for entry approval.”**
- –T.E.D. then places a call to the resident and announces the following:
 - –**“This is your Electronic Doorman, you have the following visitor.”**–The entry unit then plays back the visitor recording.
- –The Resident has the following three choices:
- –Pressing a zero “0” (programmable) activates the #1 relay in T.E.D. and grants entry.
- –T.E.D. responds with:
 - –**“I have received entry approval, please enter.”**
- –Pressing a seven “7” (programmable) rejects entry and generates the following response from T.E.D.:
 - –**“I was unable to receive entry approval, please try again later, thank you.”**
- –Pressing a nine “9” (programmable) activates the #1 relay (front door) for 15 seconds and the #2 relay (express shipment closet) for 3 minutes.
- –T.E.D. responds with:
 - –**“The express shipment closet will be unlocked for the next three minutes, please enter.”**
- –Pressing a four “4” (programmable) opens the telephone communication line between Resident and Visitor which then can result in an entry granted “0” or an entry rejected “7” and the corresponding responses from T.E.D.
- Second and third relays can be actuated by the resident to open express shipment closet, or operate multiple entrees or cameras.
- All T.E.D instructions are also displayed on the directory.



TRIGON
ELECTRONICS, INC.

PH: (951) 371-1730 • FAX (951) 371-2592 • 255 Glider Circle, Corona CA 92880